

Tersus GNSS

Oscar ProBase TAP GNSS Receiver

Overview

The Oscar ProBase TAP GNSS receiver is the new generation of Tersus's super base station system with satellite-based precise point positioning service developed by Tersus (TAP). The built-in UHF radio module supports long-distance communication and can be easily carried without an external radio. The dual transmitter for radio and network can easily be configured with a 1.54" interactive screen.

With TAP, the GNSS base station receives corrections directly from satellites, including ephemeris and satellite clock errors. The resulting fixed PPP solution can serve as a reliable coordinate reference for initializing the base station.

The Oscar ProBase TAP GNSS receiver can provide high accuracy and stable signal detection with an internal high-performance multi-constellation and multi-frequency GNSS board. The high-performance antenna can speed up the time to first fix (TTFF) and improve anti-jamming performance. The built-in large-capacity battery is detachable, and two batteries support up to 14 hours of fieldwork in Base 5W radio mode. The rugged housing protects the equipment from challenging environments.

Key Features

- ✓ Multiple constellations and frequencies
 - GPS L1C/A, L1C, L2C, L2P, L5C
 - GLONASS L1OF, L2OF, L3OC
 - BeiDou B1I, B2I, B3I, B1C, B2a, B2b
 - Galileo E1, E5a, E5b, E5AltBOC, E6
 - QZSS L1C/A, L1C, L2C, L2P, L5C
 - SBAS L1C/A, L5
 - IRNSS L5
 - L-Band
- ✓ 1792 channels
- ✓ Built-in 5W radio to support long-distance operation
- ✓ 8GB internal storage
- ✓ Up to 14 hours working in Base 5W radio mode
- ✓ IP68-rated dust- & waterproof enclosure for reliability in challenging environmental conditions
- ✓ Free subscription to Tersus Caster Service (TCS): transmit the correction data from Base to Rover
- ✓ With worldwide coverage, TAP enables centimeter-level high-precision positioning
- ✓ No need to use the network to receive corrections with TAP
- ✓ High stability TAP service, which guarantees uninterrupted transmission for 24 hours a day



Tersus GNSS

Oscar ProBase TAP GNSS Receiver

Technical Specifications

Performance

| | |
|--|------------------------------|
| Signal Tracking: | |
| GPS | L1 C/A, L1C, L2C, L2P, L5C |
| GLONASS | L1OF, L2OF, L3OC |
| BDS | B1I, B2I, B3I, B1C, B2a, B2b |
| Galileo | E1, E5a, E5b, E5AltBOC, E6 |
| QZSS | L1 C/A, L1C, L2C, L5C |
| SBAS | L1 C/A, L5 |
| L-band | |
| Channels: | 1792 |
| Single Point Positioning Accuracy (RMS): | |
| - Horizontal: | 1.5m |
| - Vertical : | 2.5m |
| DGPS Positioning Accuracy (RMS): | |
| - Horizontal: | 0.25m |
| - Vertical: | 0.5m |
| High-Precision Static (RMS): | |
| - Horizontal: | 2.5mm+0.1ppm |
| - Vertical: | 3.5mm+0.4ppm |
| Static & Fast Static (RMS): | |
| - Horizontal: | 2.5mm+0.5ppm |
| - Vertical: | 5mm+0.5ppm |
| Post Processed Kinematic (RMS): | |
| - Horizontal: | 2.5mm+1ppm |
| - Vertical: | 5mm+1ppm |
| Real Time Kinematic (RMS): | |
| - Horizontal: | 8mm+1ppm |
| - Vertical: | 15mm+1ppm |
| Initialization (Typical): | 4s ⁽¹⁾ |
| Initialization Reliability: | >99.9% ⁽²⁾ |
| Network Real Time Kinematic (RMS): | |
| - Horizontal: | 8mm+0.5ppm |
| - Vertical: | 15mm+0.5ppm |
| Observation Accuracy (zenith direction): | |
| - C/A Code: | 10cm |
| - P Code: | 10cm |
| - Carrier Phase: | 1mm |
| Timing Accuracy (RMS): | 20ns |

| | |
|---------------------------------|-----------|
| Velocity Accuracy (RMS): | 0.03m/s |
| Time To First Fix (TTFF): | |
| - ColdStart: | <30s |
| - WarmStart: | <5s |
| Re-acquisition: | <1s |
| TAP Positioning Accuracy (RMS): | |
| - Horizontal: | 15mm |
| - Vertical : | 30mm |
| TAP Convergence Time: | 3 minutes |
| TAP Coverage: | Global |
| TAP Signal Stability: | 99.99% |

System & Data

| | |
|---|---------------------------------|
| Operating System: | Linux |
| Storage: | Built-in 8GB |
| Differential Data Format: CMR, CMR+ (GPS only), RTCM2.x/3.x | |
| Data Output: | RINEX, NMEA-0183, Tersus binary |
| Data Update Rate: | 20Hz |

Software Support

Tersus Nuwa

Communication

| | |
|---------------------------------|--|
| Cellular: | 4G LTE/WCDMA/GSM |
| Cellular Bands ⁽³⁾ : | FDD LTE 1,3,7,8,20,28A 2,4,5,12,13 |
| | TDD LTE 38,40,41 |
| | WCDMA 1,8 2,5 GSM3,8 |
| Network Protocols: | Ntrip Client, Ntrip Server, TCP, Tersus Caster Service (TCS) |
| Wi-Fi: | 802.11b/g |
| Bluetooth: | 4.1 |
| NFC: | Support |
| Internal Radio | |
| RF Transmit Power: | 1W/2W/5W |
| Frequency Range: | 410MHz ~ 470MHz |

Technical Specifications

| | |
|---------------------|--|
| Operating Mode: | Half-duplex |
| Channel Spacing: | 25KHz |
| Modulation Type: | GMSK |
| Air Baud Rate: | 9600 / 19200bps |
| Distance (Typical): | 8-15km ⁽⁴⁾ |
| Radio Protocols: | |
| | TrimTalk450, TrimMark 3, South, Transparent, Satel |
| Wired Communication | |
| USB OTG: | USB 2.0 x1 |
| Serial Ports: | RS232 x1 |
| COM Baud Rate: | up to 921600bps |

Electrical

| | |
|-----------------------------------|-------------------------------|
| Input Voltage: | 9~28V DC |
| Power Consumption (Typical): | |
| Network or Radio Receive Mode: | ≈ 5W |
| Radio Transmit Mode (1W): | ≈ 8W |
| Radio Transmit Mode (2W): | ≈ 9W |
| Radio Transmit Mode (5W): | ≈ 11W |
| Lithium Battery: | 7.4V 6400mAh x2 |
| Battery Charging Temperature: | +10°C ~ +45°C |
| Battery Working Time: | up to 14 hours ⁽⁵⁾ |
| Smart Battery with Power Display: | Support |
| Electronic Bubble: | Support |

Physical

| | |
|--------------------------|--|
| Display: | 1.54" OLED |
| Buttons: | FN, ON/OFF |
| LED Indicators: | Satellite, Static, Correction data, Power |
| Dimension: | 157x157x103mm ⁽⁶⁾ |
| Weight: | ≈ 1.2kg (without battery) ≈ 1.4kg (with a battery) ⁽⁶⁾ |
| Operating Temperature: | -40°C ~ +70°C |
| Storage Temperature: | -55°C ~ +85°C |
| Relative Humidity: | 100% not condensed |
| Dust- & Waterproof: | IP68 |
| Pole Drop onto Concrete: | 2m |
| Vibration: | MIL-STD-810G, FIG 514.6C-1 |
| Warranty period: | ONE Year |

Note:

(1) The initialization time depends on various factors, including the number of satellites, observation time, atmospheric conditions, multi-path, obstructions, satellite geometry, etc.

(2) The initialization reliability may be affected by atmospheric conditions, signal multipath, and satellite geometry.

(3) Depending on version. In order Europe | American version.

(4) The distance depends on the environment and antenna type. In an urban environment, a short rod antenna can reach up to 8 km, and a high-gain antenna can reach up to 15 km. In optimal conditions, the range can exceed 15 km. However, in challenging environments such as wooded and suburban areas, the range will be less than 8 km.

(5) Oscar ProBase TAP uses one battery at a time, the other is a substitute. Each battery lasts up to 7 hours when Oscar ProBase TAP works in Base 5W radio mode. Two batteries add up to 14 hours of continuous use. The working time of the battery is related to the working environment, working temperature and battery life.

(6) The actual size/weight may vary depending on the manufacturing process and measurement method.

Website: www.tersus-gnss.com
Sales Inquiry: sales@tersus-gnss.com
Technical Support: support@tersus-gnss.com

Information is subject to change without notice.
© Copyright 2025 Tersus GNSS Inc.